


## DESCRIPTION

Specification grade, wet listed 71 watt MR16 lamp fixture. The 60° cutoff to lamp and lamp image provides a glare free, smooth distribution of light. For use with all halogen MR16 lamps in either open or cover glass varieties. Units small size is ideal for tight construction areas. Insulation must be kept 3" away from sides and top of fixture. **Optical element can be changed after installation to provide a variety of distributions. e.g. into an Adjustable**



## SPECIFICATION FEATURES

**A...Reflector**

.040 thick aluminum spun parabolic reflector in Clear, Gold, Haze, Warm Haze, Black Alzak® finish, painted gloss white or matte white. Special cone colors listed below. .125 thick tempered glass protects lamp from direct spray of water and is retained during relamping.

**B...Flange**

Self flange reflector or die-cast flange with either matte white or clear coat finish. Die-cast flanges are easily removed for field painting. Elements are keyed for proper insertion.

**C...Lens**

Soft focus lens standard for smooth beam patterns. Up to two filter media can be used which are retained during relamping.

**D...Attachment**

Positive torsion springs pull flange tight to ceiling. Mechanical light trap eliminates spill light at edge of flange or reflector.

**E...Socket**

GX5.3 base for Bi-pin MR16 lamps. Fixed socket height ensures consistent lamp position and back light shield keeps interior of fixture dark.

**F...Transformer**

Truvolt™ toroidal transformer with dual-output taps for proper 12.0V operation. Dimmer tap compensates for inherent voltage loss from dimmers, resulting in 30% more lumens than traditional laminated transformers. Toroidal design, with 90% or greater efficiency, features a rolled one-piece continuous core of M3 grade grain oriented silicon steel complete with an integral thermal to protect against overheating and ensure quiet operation.

For dimming, use dimmers rated for electromagnetic transformers. **Transformer is warranted for 5 years and is serviceable from below ceiling.**

Note: If a dimming system is operated for construction lighting in its "shunt" mode, i.e. bypassing the dimmer modules, for an extended period of time, fixtures with the dual-tap toroidal transformer should be operated on the "Switched Fixture" output until the dimmers are in use. Operating fixtures on the "Dimmed Fixture" output with a full 120v input for an extended period will overdrive the lamp and cause shortened lamp life.

**G...Frame/Housing**

Hot dipped galvanized 20 gauge steel frame with built in 1/2 inch plaster lip. Gunsights allow for consistent alignment. Matte black housing interior.

**H...Junction Box**

18 cubic inches, listed for 4#12 AWG or 6#14 AWG 90 C additional feed through conductors, has three 1/2 inch pryouts.

**I...Bar Hangers**


No Flex® bar hangers with positive locking, for use with wood, engineered wood and steel frame joists spaced up to 24" O.C. ship with platform. For use in T-bar ceilings order accessory MBCLP. Nailless barb and locator lip provide consistent installation height.

**J...Codes**

Thermally protected, IP labeled . Meets Air tight requirements, 1995 CABO Model Energy Code.

**K...Labels**


UL and cUL listed, standard wet label, IBEW union made.



# PN3MR E3SR

71 W MR 16

3" SHOWER  
DOWNLIGHT



## ENERGY DATA

120V Input

Lamp Watts	Input Watts	Operating Current
20	23	.19
35	41	.34
37	42	.35
42	47	.39
50	57	.48
65	70	.58
71	77	.64
75	81	.68

## ORDERING INFORMATION

Complete unit consists of a platform and element

Platform	Optical Element	Finish	Flange	Accessories
<b>PN3MR</b>	<b>E3SR</b>			
PN3MR = 3" Non-IC Low Voltage Housing PN3MR REMOTE = 3" Non-IC Housing for Remote Transformer	Element E3SR = 3" MR16 Lensed Downlight Reflector	<b>Standard</b> C=Clear H=Haze G=Gold WMH=Warm Haze W=Gloss White MW= Matte White B= Black <b>Custom</b> K=Cognac KH=Cognac Haze	CC=Chocolate CCH=Chocolate Haze BU=Blush BUH=Blush Haze GP=Graphite GPH=Graphite Haze PN=Pine PNH=Pine Haze SK=Sky SKH=Sky Haze	Blank= Matte White die-cast SF= Self Flange RAW= Natural Die-cast SFWF= Self Flange Painted White MBCLP = 40 Push On T Bar Clips (for 10 Units) PLE3 = Plaster Lip Extension for Max 2" Thick Ceiling LSPD = Spread Lens LLNR = Linear Spread Lens LUV = UV Reduction Lens LLPINK = Light Pink Lens LLSTRAW = Light Straw Lens L27K = 2700K dichroic filter LDAY = Daylight LSPINK = Surprise Pink Lens LPLAV = Pale Lavender Lens LHEX= Hex Cell Louver

# PHOTOMETRICS


Unit Number: **PN3MR-E3SR**

## PN3MR-E3SRC

Test No. H21086  
Lamp: GE 71MR16/C/FL40  
Lumens: 1200  
Cutoff: 60°  
Spacing: 0.6  
Efficiency: 68.8%  
Unit LPW: 11.6

Candelas	
Vertical Angle	CD
90	0
85	0
75	0
65	0
55	11
45	15
35	121
25	559
15	1124
5	1677
0	1912

## Distribution



## Luminance

Degree	cd/m²
85°	0
75°	0
65°	0
55°	3089
45°	3416

## Cone of Light

Distance to Illuminated Plane	Initial Nadir Footcandles	Beam Diameter
4'6"	94	2'6"
5'6"	63	3'0"
6'6"	45	4'0"
8'0"	30	4'6"
10'0"	19	6'0"
12'0"	13	7'0"

## Zonal Lumen Summary

Zone	Lumens	%Lamp	%Luminaire
0-30	716	59.7	86.7
0-40	798	66.5	96.6
0-60	826	68.8	100.0
0-90	826	68.8	100.0
90-180	0	0.0	0.0
0-180	826	68.8	100.0

## Coefficient of Utilization


Ceiling Reflectance	80%				70%				50%				30%				0%
Wall Reflectance	70	50	30	10	50	10	50	10	50	10	50	10	50	10	50	10	0
Room Cavity Ratio	0	82	82	82	82	80	80	80	76	76	76	76	73	73	73	69	69
1	79	78	76	75	76	74	74	72	74	72	71	70	71	70	67	67	67
2	77	74	72	71	73	70	71	68	69	68	69	67	69	67	64	64	64
3	74	71	69	67	70	66	69	65	67	65	67	64	67	64	63	63	63
4	72	68	66	64	68	63	66	63	66	63	65	62	65	62	61	61	61
5	70	66	63	61	65	61	64	60	64	60	63	60	63	60	58	58	58
6	68	64	61	59	63	58	62	58	62	58	61	58	61	58	57	57	57
7	66	61	58	56	61	56	60	56	60	56	59	55	59	55	55	55	55
8	64	59	56	54	59	54	58	54	58	54	57	54	57	54	53	53	53
9	62	57	54	52	57	52	56	52	56	52	55	52	55	52	51	51	51
10	60	55	52	50	55	50	54	50	54	50	54	50	54	50	49	49	49

## PN3MR-E3SRC

Test No. H21085  
Lamp: GE 50MR16/C/FL40  
Lumens: 880  
Cutoff: 60°  
Spacing: 0.5  
Efficiency: 65.9%  
Unit LPW: 11.5

Candelas	
Vertical Angle	CD
90	0
85	0
75	0
65	0
55	8
45	11
35	67
25	343
15	842
5	1469
0	1715

## Distribution



## Luminance

Degree	cd/m²
85°	0
75°	0
65°	0
55°	2246
45°	2505

## Cone of Light

Distance to Illuminated Plane	Initial Nadir Footcandles	Beam Diameter
4'6"	84	2'0"
5'6"	56	2'6"
6'6"	40	3'0"
8'0"	27	4'0"
10'0"	17	5'0"
12'0"	12	6'0"

## Zonal Lumen Summary

Zone	Lumens	%Lamp	%Luminaire
0-30	517	58.7	89.1
0-40	562	63.9	96.9
0-60	580	65.9	100.0
0-90	580	65.9	100.0
90-180	0	0.0	0.0
0-180	580	65.9	100.0

## Coefficient of Utilization

Ceiling Reflectance	80%				70%				50%				30%				0%
Wall Reflectance	70	50	30	10	50	10	50	10	50	10	50	10	50	10	50	10	0
Room Cavity Ratio	0	78	78	78	78	77	77	77	73	73	73	73	70	70	70	66	66
1	76	75	73	72	73	71	71	69	71	69	68	67	68	67	64	64	64
2	74	71	70	68	70	67	68	66	68	66	66	64	66	64	62	62	62
3	72	69	67	65	68	64	66	63	66	63	65	62	65	62	61	61	61
4	70	66	64	62	66	62	64	61	64	61	63	60	63	60	59	59	59
5	67	64	61	59	63	59	62	59	62	59	61	58	61	58	57	57	57
6	66	62	59	57	61	57	61	57	61	57	60	57	60	57	56	56	56
7	64	60	57	55	59	55	59	55	59	55	58	55	58	55	54	54	54
8	62	58	55	53	57	53	57	53	57	53	56	53	56	53	52	52	52
9	60	56	53	52	56	52	55	51	55	51	55	51	55	51	50	50	50
10	59	54	52	50	54	50	54	50	54	50	53	50	53	50	49	49	49

## Notes and Formulas:

**Luminance:** To convert cd/m² to footlamberts, multiply by 0.2919

### Cone of Light:

- Beam diameter is to 50% of maximum footcandles, rounded to the nearest half-foot.
- Footcandle values are initial. Apply appropriate light loss factors where necessary.

See pages 64-65 of Iris Catalog

### CU Notes/Formulas:

- $\text{maintained illuminance} = \frac{\text{lamp lumens} \times \text{CU} \times \text{light loss factors}}{\text{room area}}$
- $\text{total number of luminaires} = \frac{\text{total room area} \times \text{maintained illuminance}}{\text{lamp lumens} \times \text{CU} \times \text{light loss factors}}$
- CU data based on 20% effective floor cavity reflectance.

Note: Specifications and Dimensions subject to change without notice.

Visit our web site at [www.cooperlighting.com](http://www.cooperlighting.com)



Customer First Center 1121 Highway 74 South Peachtree City, GA 30269 770.486.4800 FAX 770.486.4801 AD030818  
Cooper Lighting 5925 McLaughlin Rd. Mississauga, Ontario, Canada L5R 1B8 905.507.4000 FAX 905.568.7049