

Compatible 110-120 VAC Electronic Transformer/Dimmer Combinations

Brand	Model	Input Voltage	Power (watts)	Voltage (V)	 Diva DELV-300P/303P   Maestro MAELV - 600   Skylark SELV 300PH   Nova NELV 450   Decora 6615P 																			
					# of modules per transformer				# of modules per transformer				# of modules per transformer				# of modules per transformer				# of modules per transformer			
					1	2	3	4	1	2	3	4	1	2	3	4	1	2	3	4	1	2	3	4
	CV90001 (CV-10/75-12)	120 VAC, 50-60 Hz	75	12	> 5%	> 5%	> 5%	> 5%	OK	OK	OK	OK	> 5%	> 5%	> 5%	> 5%	OK	OK	OK	OK	> 5%	> 5%	> 5%	> 5%
	CV90038	120 VAC, 50-60 Hz	75	24	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X	X
	Pony PET-120-12-75	120 VAC, 50-60 Hz	75	12	> 5%	> 5%	> 5%	> 5%	OK	OK	OK	OK	OK	OK	OK	OK	OK	OK	OK	OK	< max	OK	OK	OK
	RS12-60M(LED)	120 VAC, 50-60 Hz	60	12	> 5%	> 5%	> 50%	> 50%	OK	OK	> 5%	> 5%	> 5%	> 5%	> 50%	> 50%	OK	OK	X	X	X	X	X	X
	RS12-60M	120 VAC, 50-60 Hz	60	12	> 33%	OK	OK	OK	OK	OK	> 5%	OK	OK	OK	OK	OK	X	OK	OK	OK	X	X	OK	OK
	RS12-80M	120 VAC, 50-60 Hz	80	12	OK	OK	OK	OK	OK	OK	OK	OK	OK	OK	OK	OK	X	OK	OK	OK	X	X	OK	OK
	RS12-80BFS	120 VAC, 50-60 Hz	80	12	OK	OK	OK	OK	< max	OK	OK	OK	OK	OK	OK	OK	OK	OK	OK	> 33%	OK	OK	OK	OK
	RS12-60	120 VAC, 50-60 Hz	80	12	> min	> min	> 5%	> 5%	> 5%	> 5%	> 5%	> 5%	> min	> min	> min	> 5%	OK	OK	OK	OK	< max	OK	OK	OK
	LET-60	120 VAC, 60 Hz	60	12	OK	OK	OK	OK	OK	OK	OK	OK	> 50%	OK	OK	OK	X	OK	OK	OK	< max	OK	OK	OK
	LET-75	120 VAC, 60 Hz	75	12	X	OK	OK	OK	> min	OK	OK	OK	> 50%	OK	OK	OK	X	OK	OK	OK	< max	< max	OK	OK
	LET-75-24-R	120 VAC, 60 Hz	75	24	X	X	> 15%	OK	X	X	OK	OK	> 30%	> 30%	OK	OK	> 25%	> 25%	OK	OK	X	X	> 30%	OK
	316-0047	120 VAC, 60 Hz	75	12	> 10%	> 10%	OK	OK	X	X	X	X	X	> min	OK	OK	X	OK	OK	OK	> 10%	> 10%	OK	OK

Compatible 110-120 VAC Magnetic Transformer/Dimmer Combinations

Brand	Model	Input Voltage	Power (watts)	Voltage (V)	 Diva DELV-600P   Ariadni AVLV-600P   VPM06 1L 											
					# of modules per transformer				# of modules per transformer				# of modules per transformer			
					1	2	3	4	1	2	3	4	1	2	3	4
	T1-79203-SR	120 VAC, 60 Hz	300	12	OK	OK	OK	OK	OK	OK	OK	OK	< min	< min	< min	< min
	M60L12	120 VAC, 60 Hz	60	12	< min	< min	< min	< min	< min	< min	< min	< min	X	X	X	X
	1022-12	120 VAC, 60 Hz	100	12	< max	< max	< max	OK	OK	OK	OK	OK	X	X	X	X
	1025-12	120 VAC, 60 Hz	500	12	OK	OK	< max	< max	OK	OK	OK	OK	X	X	X	X

Non Dimmed 110 - 120 VAC **Electronic** Transformer Compatibility

Brand	Model	Input Voltage	Power (watts)	Voltage (V)	# of modules per transformer			
					1	2	3	4
 	CV90001 (CV-10/75-12)	120 VAC, 50-60 Hz	75	12	OK	OK	OK	OK
	CV90038	120 VAC, 50-60 Hz	75	24	X	X	X	X
	Pony PET-120-12-75	120 VAC, 50-60 Hz	75	12	OK	OK	OK	OK
	RS12-60M(LED)	120 VAC, 50-60 Hz	60	12	X	X	X	X
	RS12-60M	120 VAC, 50-60 Hz	60	12	OK	OK	OK	OK
	RS12-80M	120 VAC, 50-60 Hz	80	12	OK	OK	OK	OK
	RS12-80BFS	120 VAC, 50-60 Hz	80	12	X	X	X	X
	RS12-60	120 VAC, 50-60 Hz	80	12	OK	OK	OK	OK
	LET-60	120 VAC, 60 Hz	60	12	OK	OK	OK	OK
	LET-75	120 VAC, 60 Hz	75	12	OK	OK	OK	OK
	LET-75-24-R	120 VAC, 60 Hz	75	24	X	X	X	X
	316-0047	120 VAC, 60 Hz	75	12	X	OK	OK	OK

Non Dimmed 110 - 120 VAC **Magnetic** Transformer Compatibility

Brand	Model	Input Voltage	Power (watts)	Voltage (V)	# of modules per transformer			
					1	2	3	4
	T1-79203-SR	120 VAC, 60 Hz	300	12	OK	OK	OK	OK
	L012-1-712	120 VAC, 60 Hz	12	12	OK	X	X	X
	L020-1-712	120 VAC, 60 Hz	20	12	OK	OK	X	X
	M60L12	120 VAC, 60 Hz	60	12	OK	OK	OK	OK
 	486-0440582T	120 VAC, 60 Hz	50	12	OK	OK	OK	OK
	1022-12	120 VAC, 60 Hz	100	12	OK	OK	OK	OK
	1025-12	120 VAC, 60 Hz	500	12	OK	OK	OK	OK

Compatible 277 VAC Electronic Transformer/Dimmer Combinations



PLV - 527 (277V)



in combination with dimmer

Brand	Model	Input Voltage	Power (watts)	Voltage (V)	# of modules per transformer				
					1	2	3	4	5
	RS12-80-277M	277 VAC, 50-60Hz	80	12	X	OK	OK	OK	OK
	VJ12-75	277 VAC, 50-60Hz	75	12	OK	OK	OK	OK	OK
	LET-75-277R	277 VAC, 50-60Hz	60	12	X	X	OK	OK	OK

Non Dimmed 277 VAC **Electronic** Transformer Compatibility

Brand	Model	Input Voltage	Power (watts)	Voltage (V)	# of modules per transformer				
					1	2	3	4	5
	RS12-80-277M	277 VAC, 50-60Hz	80	12	OK	OK	OK	OK	OK
	VJ12-75	277 VAC, 50-60Hz	75	12	OK	OK	OK	OK	OK
	LET-75-277R	277 VAC, 50-60Hz	60	12	OK	OK	OK	OK	OK