

1000 Lumens / 250mA / D010

Dimmer Make	Dimmer Series	Dimmer Model #	Types of Dimmer	Minimum Lamps or Luminaires (per circuit)	Maximum Recommended Luminaires (per circuit) at 120V	Maximum Recommended Luminaires (per circuit) at 277V	Max Dimming percentage (%)	Min Dimming percentage (%)	Low End Start Time
Eaton	Slide Dimmer	SF10P	0-10v	1	94	120	100	1	>1S
Eaton	Decorator Dimmer	DF10P	0-10v	1	94	120	100	1	>1S
Leviton	Illumatech	IP710-DL	0-10v	1	93	93	97	1	>1S
Lutron	NTFTV	NOVA T	0-10v	1	100	100	100	1	>1S
Lutron	DIVA	DVTV	0-10v	1	100	100	100	1	>1S
Eaton	iLumin	SC277-06	0-10v	1	148	303	100	1	>1S
Eaton	Greengate	CK4A	0-10v	1	186	303	100	1	>1S

1500 Lumens / 350mA / D010

Dimmer Make	Dimmer Series	Dimmer Model #	Types of Dimmer	Minimum Lamps or Luminaires (per circuit)	Maximum Recommended Luminaires (per circuit) at 120V	Maximum Recommended Luminaires (per circuit) at 277V	Max Dimming percentage (%)	Min Dimming percentage (%)	Low End Start Time
Eaton	Slide Dimmer	SF10P	0-10v	1	63	85	100	1	>1S
Eaton	Decorator Dimmer	DF10P	0-10v	1	63	85	100	1	>1S
Leviton	Illumatech	IP710-DL	0-10v	1	63	77	99	1	>1S
Lutron	NTFTV	NOVA T	0-10v	1	98	100	100	1	>1S
Lutron	DIVA	DVTV	0-10v	1	98	100	100	1	>1S
Eaton	iLumin	SC277-06	0-10v	1	98	213	100	1	>1S
Eaton	Greengate	CK4A	0-10v	1	123	266	100	1	>1S

2000 Lumens / 500mA / D010

Dimmer Make	Dimmer Series	Dimmer Model #	Types of Dimmer	Minimum Lamps or Luminaires (per circuit)	Maximum Recommended Luminaires (per circuit) at 120V	Maximum Recommended Luminaires (per circuit) at 277V	Max Dimming percentage (%)	Min Dimming percentage (%)	Low End Start Time
Eaton	Slide Dimmer	SF10P	0-10v	1	45	62	100	1	>1S
Eaton	Decorator Dimmer	DF10P	0-10v	1	45	62	100	1	>1S
Leviton	Illumatech	IP710-DL	0-10v	1	45	56	100	1	>1S
Lutron	NTFTV	NOVA T	0-10v	1	71	111	100	1	>1S
Lutron	DIVA	DVTV	0-10v	1	71	115	100	1	>1S
Eaton	iLumin	SC277-06	0-10v	1	71	160	100	1	>1S
Eaton	Greengate	CK4A	0-10v	1	88	200	100	1	>1S

3000 Lumens / 700mA / D010

Dimmer Make	Dimmer Series	Dimmer Model #	Types of Dimmer	Minimum Lamps or Luminaires (per circuit)	Maximum Recommended Luminaires (per circuit) at 120V	Maximum Recommended Luminaires (per circuit) at 277V	Max Dimming percentage (%)	Min Dimming percentage (%)	Low End Start Time
Eaton	Slide Dimmer	SF10P	0-10v	1	34	48	100	1	<1S
Eaton	Decorator Dimmer	DF10P	0-10v	1	34	48	100	1	<1S
Leviton	Illumatech	IP710-DL	0-10v	1	34	43	96	1	<1S
Lutron	NTFTV	NOVA T	0-10v	1	55	120	100	1	<1S
Lutron	DIVA	DVTV	0-10v	1	55	120	100	1	<1S
Eaton	iLumin	SC277-06	0-10v	1	55	125	100	1	<1S
Eaton	Greengate	CK4A	0-10v	1	69	156	100	1	<1S

4000 Lumens / 1050mA / D010

Dimmer Make	Dimmer Series	Dimmer Model #	Types of Dimmer	Minimum Lamps or Luminaires (per circuit)	Maximum Recommended Luminaires (per circuit) at 120V	Maximum Recommended Luminaires (per circuit) at 277V	Max Dimming percentage (%)	Min Dimming percentage (%)	Low End Start Time
Eaton	Slide Dimmer	SF10P	0-10v	1	23	32	100	1	<1S
Eaton	Decorator Dimmer	DF10P	0-10v	1	23	32	100	1	<1S
Leviton	Illumatech	IP710-DL	0-10v	1	23	29	97	1	<1S
Lutron	NTFTV	NOVA T	0-10v	1	36	84	100	1	<1S
Lutron	DIVA	DVTV	0-10v	1	36	84	100	1	<1S
Eaton	iLumin	SC277-06	0-10v	1	36	84	100	1	<1S
Eaton	Greengate	CK4A	0-10v	1	45	105	100	1	<1S

1000 Lumens / 250mA / D010TR / 0-10V dimming

Dimmer Make	Dimmer Series	Dimmer Model #	Types of Dimmer	Minimum Lamps or Luminaires (per circuit)	Maximum Recommended Luminaires (per circuit) at 120V	Maximum Recommended Luminaires (per circuit) at 277V	Max Dimming percentage (%)	Min Dimming percentage (%)	Low End Start Time
Eaton	Slide Dimmer	SF10P	0-10v	1	93	121	100	3	>1S
Eaton	Decorator Dimmer	DF10P	0-10v	1	93	121	100	3	>1S
Leviton	Illumatech	IP710-DL	0-10v	1	93	93	100	3	>1S
Lutron	NTFTV	NOVA T	0-10v	1	100	100	100	4	>1S
Lutron	DIVA	DVTV	0-10v	1	100	100	100	3	>1S
Eaton	iLumin	SC277-06	0-10v	1	148	297	100	3	>1S
Eaton	Greengate	CK4A	0-10v	1	186	333	100	3	>1S

1500 Lumens / 350mA / D010TR / 0-10V dimming

Dimmer Make	Dimmer Series	Dimmer Model #	Types of Dimmer	Minimum Lamps or Luminaires (per circuit)	Maximum Recommended Luminaires (per circuit) at 120V	Maximum Recommended Luminaires (per circuit) at 277V	Max Dimming percentage (%)	Min Dimming percentage (%)	Low End Start Time
Eaton	Slide Dimmer	SF10P	0-10v	1	68	89	100	6	<1S
Eaton	Decorator Dimmer	DF10P	0-10v	1	68	89	100	6	<1S
Leviton	Illumatech	IP710-DL	0-10v	1	68	81	100	6	<1S
Lutron	NTFTV	NOVA T	0-10v	1	100	100	100	6	<1S
Lutron	DIVA	DVTV	0-10v	1	100	100	100	6	<1S
Eaton	iLumin	SC277-06	0-10v	1	109	224	100	6	<1S
Eaton	Greengate	CK4A	0-10v	1	136	280	100	6	<1S

2000 Lumens / 500mA / D010TR / 0-10V dimming

Dimmer Make	Dimmer Series	Dimmer Model #	Types of Dimmer	Minimum Lamps or Luminaires (per circuit)	Maximum Recommended Luminaires (per circuit) at 120V	Maximum Recommended Luminaires (per circuit) at 277V	Max Dimming percentage (%)	Min Dimming percentage (%)	Low End Start Time
Eaton	Slide Dimmer	SF10P	0-10v	1	46	60	100	3	<1S
Eaton	Decorator Dimmer	DF10P	0-10v	1	46	60	100	3	<1S
Leviton	Illumatech	IP710-DL	0-10v	1	46	54	100	3	<1S
Lutron	NTFTV	NOVA T	0-10v	1	73	100	100	3	<1S
Lutron	DIVA	DVTV	0-10v	1	73	100	100	3	<1S
Eaton	iLumin	SC277-06	0-10v	1	73	150	100	3	<1S
Eaton	Greengate	CK4A	0-10v	1	91	188	100	3	<1S

3000 Lumens / 700mA / D010TR / 0-10V dimming

Dimmer Make	Dimmer Series	Dimmer Model #	Types of Dimmer	Minimum Lamps or Luminaires (per circuit)	Maximum Recommended Luminaires (per circuit) at 120V	Maximum Recommended Luminaires (per circuit) at 277V	Max Dimming percentage (%)	Min Dimming percentage (%)	Low End Start Time
Eaton	Slide Dimmer	SF10P	0-10v	1	33	45	100	7	<1S
Eaton	Decorator Dimmer	DF10P	0-10v	1	33	45	100	7	<1S
Leviton	Illumatech	IP710-DL	0-10v	1	33	41	100	7	<1S
Lutron	NTFTV	NOVA T	0-10v	1	53	100	100	8	<1S
Lutron	DIVA	DVTV	0-10v	1	53	100	100	7	<1S
Eaton	iLumin	SC277-06	0-10v	1	53	114	100	7	<1S
Eaton	Greengate	CK4A	0-10v	1	66	142	100	7	<1S

4000 Lumens / 1050mA / D010TR / 0-10V dimming

Dimmer Make	Dimmer Series	Dimmer Model #	Types of Dimmer	Minimum Lamps or Luminaires (per circuit)	Maximum Recommended Luminaires (per circuit) at 120V	Maximum Recommended Luminaires (per circuit) at 277V	Max Dimming percentage (%)	Min Dimming percentage (%)	Low End Start Time
Eaton	Slide Dimmer	SF10P	0-10v	1	22	30	100	5	<1S
Eaton	Decorator Dimmer	DF10P	0-10v	1	22	30	100	5	<1S
Leviton	Illumatech	IP710-DL	0-10v	1	22	27	100	5	<1S
Lutron	NTFTV	NOVA T	0-10v	1	35	75	100	5	<1S
Lutron	DIVA	DVTV	0-10v	1	35	75	100	5	<1S
Eaton	iLumin	SC277-06	0-10v	1	35	75	100	5	<1S
Eaton	Greengate	CK4A	0-10v	1	44	94	100	5	<1S

Manufacturer	Series	Model	Minimum Luminaires (per circuit) ¹	Maximum Luminaires (per circuit) ¹	Minimum Measured Light Output	Maximum Measured Light Output	Low End Start Time	Additional Comments
EATON	Decorator	DAL06P	1	23	5%	99%	<1s	
EATON	Smart	AAL06P	1	23	5%	99%	<1s	
EATON	Toggle	TAL06P	1	23	5%	100%	<1s	
EATON	Slide	SAL06P	1	23	5%	100%	<1s	Slight Shimmer
EATON	Slide	SLC03P	1	23	5%	99%	<1s	
EATON	Toggle	DLC03P	1	23	5%	99%	<1s	
EATON	iLumin	SC277-06-UN	1	37	5%	100%	<1s	Slight Shimmer
Vantage	Enclosure Module	SDM12-EM	1	34	2%	95%	>1s	2s Start Time
Vantage	Enclosure Module	UDIMMOD-FWD	1	65	2%	96%	>1s	2s Start Time
Vantage	Enclosure Module	UDIMMOD-REV	1	65	2%	96%	>1s	2s Start Time
Vantage	ScenePoint	DS/RD	1	10	2%	96%	>1s	2s Start Time
Vantage	DIN Enclosure	LVRS8-DIN(0-10v)	1	54	3%	95%	>1s	2s Start Time
Creston	iLux	CLS-EXP-DIM	--	--	2%	100%	--	
Creston	iLux	CLS-EXP-DIMU	--	--	5%	100%	--	
Creston	CLX	CLX-1DIM4	--	--	4%	100%	--	
Creston	CLX	CLX-1DIM8	--	--	4%	100%	--	
Creston	CLX	CLX-2DIM2	--	--	4%	100%	--	
Creston	CLX	CLX-2DIM8	--	--	4%	100%	--	
Creston	DIN Rail	DIN-1DIM4	--	--	2%	100%	--	
Creston	DIN Rail	DIN-1DIMU4	--	--	6%	100%	--	
Creston	Cameo Express	CLW-DIMEX-E	--	--	1%	100%	--	
Creston	Cameo	CLW-DIMEX-P	--	--	1%	100%	--	
Creston	Cameo Express	CLW-DIMSWEX-E	--	--	1%	100%	--	
Creston	Cameo	CLW-DIMSWEX-P	--	--	1%	100%	--	
Creston	Prodigy	P-DIMEX	--	--	1%	100%	--	
Creston	Green Light	GLX-DIM6	--	--	3%	100%	--	
Creston	Green Light Express	GLXX-2DIM8	--	--	3%	100%	--	
Creston	Cameo Express	CLW-DELVEX-E	--	--	2%	100%	--	
Creston	Cameo	CLW-DELVEX-P	--	--	2%	100%	--	
Creston	CLX	CLX-1DIMU4	--	--	2%	100%	--	
Creston	CLX	CLX-2DIMU8	--	--	2%	100%	--	
Creston		GL-EXP-DIMU-DALI	--	--	5%	100%	--	
Creston		GL-EXP-DIMU-CN	--	--	5%	100%	--	
Lutron	Maestro	MACL-153M	1	10	16%	95%	<1s	
Lutron	RadioRA 2	RRD-10ND	1	9	17%	99%	<1s	
Lutron	HomeWorks QS	HQRD-10ND	1	9	17%	99%	<1s	
Lutron	RadioRA 2	RRD-6NA	1	10	17%	99%	<1s	
Lutron	HomeWorks QS	HQRD-6NA	1	10	17%	99%	<1s	
Lutron	HomeWorks	HxD-6ND	1	2	19%	97%	<1s	
Lutron	Stanza	SZ-6ND	1	8	19%	97%	<1s	

Manufacturer	Series	Model	"Minimum Luminaires (per circuit)"	"Maximum Luminaires (per circuit)"	Minimum Measured Light Output	Maximum Measured Light Output	Low End Start Time	Additional Comments
Lutron	Panel module	PHPM-PA with Grafik Eye QS Main Unit	1	22	18%	99%	>1s	
Lutron	Panel Module	PHPM-WBX with 3-wire fluorescent control	1	24	19%	99%	>1s	
Lutron	Panel Module	HW/LP-RPM-4A-120	1	15	18%	99%	>1s	
Lutron	Panel Module	HW/LP-RPM-4U-120	1	11	19%	99%	>1s	
Lutron	Grafik QS/Wallbox Power Module	"Grafik Eye QS Main Unit Family/ LQRJ-WPM-6P"	1	11	20%	99%	<1s	
Lutron	Panel Module	GP (Harrier) Card	1	11	20%	99%	>1s	
Lutron	Maestro Sensor	MSCL-OP153M(T2)	1	10	20%	95%	<1s	
Lutron	Maestro Sensor	MSCL-VP153M(T2)	1	10	20%	95%	<1s	
Lutron	Grafik Eye 3000/HomeWorks	Grafik Eye 3000 Family/HWI-WPM-6D-120	1	11	20%	99%	<1s	
Lutron	Caseta Wireless	PD-6WCL (SD11)	1	10	12%	98%	<1s	
Lutron	RadioRA 2	RRD-6CL (R3)	1	10	14%	96%	<1s	
Lutron	Maestro Wireless	MRF2-6CL (M6)	1	10	14%	96%	<1s	
Lutron	HomeWorks QS	HQRD-6CL (H2)	1	10	14%	96%	<1s	
Lutron	HomeWorks QS	HQRA-6CL (H2)	1	10	14%	96%	<1s	
Lutron	RadioRA 2	RRD-H6BRL (with neutral)	1	7	15%	99%	>1s	
Lutron	HomeWorks QS	HQRD-H6BRL (with neutral)	1	7	15%	99%	>1s	
Lutron	HomeWorks QS/myRoom	LQSE-4A1-D	1	2	18%	99%	>1s	
Lutron	HomeWorks QS/myRoom	MQSE-4A1-D	1	2	18%	99%	>1s	
Lutron	HomeWorks QS/myRoom	MQSE-3A1	1	2	18%	99%	>1s	
Lutron	HomeWorks QS/myRoom	MQSE-2A1-D	1	2	18%	99%	>1s	

Manufacturer	Series	Model	Minimum Luminaires (per circuit)"	Maximum Luminaires (per circuit)"	Minimum Measured Light Output	Maximum Measured Light Output	Low End Start Time	Additional Comments
EATON	Toggle	TI061	1	46	3%	94%	>1s	3s Turn on Time at Low End Dimming
EATON	Aspire	9530AW	1	46	3%	100%	>1s	3s Turn on Time at Low End Dimming
EATON	Rotary	RI061	1	46	27%	100%	<1s	
EATON	Slide	SF8AP	1	74	6%	100%	<1s	Slight Shimmer
EATON	Decorator	DE06P	1	46	2%	95%	>1s	4s Turn on Time at Low End Dimming
Lutron	Toggler	TG-600P	1	46	5%	98%	<1s	
Lutron	Diva	DV-600P	1	46	10%	99%	<1s	
Lutron	Skylark	S-600P	1	46	5%	99%	<1s	
Lutron	Skylark Contour	CT103P	1	77	5%	99%	<1s	
Lutron	Diva	DV603P	1	46	4%	99%	<1s	
Lutron	Nova T	NTFTU-5A	1	46	6%	98%	>1s	3s Turn on Time at Low End Dimming, Slight Shimmer
Lutron	Maestro	MAELV600	1	46	5%	88%	<1s	
Lutron	Diva	DVELV303P	1	23	5%	68%	<1s	
Lutron	Skylark	SELV300P	1	23	5%	72%	<1s	
Leviton	SureSlide	6674	1	11	4%	99%	<1s	
Leviton	Illumatech	IPL06	1	11	4%	98%	<1s	
Leviton	Decora	6673	1	46	22%	97%	<1s	Slight Shimmer
Leviton	SureSlide	6631-2	1	46	3%	98%	<1s	Slight Shimmer
Leviton		IPI06	1	46	5%	98%	<1s	Slight Shimmer
Leviton	Vizia	VP106	1	46	5%	98%	<1s	
Leviton	Sure Slide	6633-P	1	46	5%	98%	<1s	Slight Shimmer
Leviton	Plug In Lamp Dimmer	TBI03	1	23	7%	100%	<1s	Slight Shimmer
Leviton	Vizia	VPE06	1	46	4%	99%	<1s	
Leviton	Illumatech	IPE04	1	23	5%	99%	<1s	
Leviton	Vizia	VZE04	1	31	1%	97%	<1s	
Legrand	Pass&Seymour Harmony	H703PTUW	1	34	3%	99%	<1s	
Hubbell	TradeSelect	RD600PDK	1	46	7%	99%	<1s	Slight Shimmer
Lutron	Contour	CT-103P	1	77	5%	99%	<1s	
Lutron	Contour	CT-600P	1	46	5%	99%	<1s	Slight Shimmer
Lutron	Rotary	D-600P	1	46	4%	99%	<1s	Slight Shimmer
Lutron	Diva	DV-600P	1	46	5%	99%	<1s	Slight Shimmer
Lutron	Glyder	GL-600P	1	46	5%	99%	<1s	
Lutron	Lumia	LG-600PH	1	46	5%	99%	<1s	
Lutron	Nova	N-600	1	46	8%	99%	<1s	Slight Shimmer
Lutron	Skylark	S-600P	1	46	5%	99%	<1s	
Lutron	Ariadni	AYLV-600P	1	34	0%	99%	>1s	5s Turn on Time at Low End Dimming

Manufacturer	Series	Model	"Minimum Luminaires (per circuit)"	"Maximum Luminaires (per circuit)"	Minimum Measured Light Output	Maximum Measured Light Output	Low End Start Time	Additional Comments
Lutron	Glyder	GLV-600	1	34	5%	99%	<1s	
Lutron	Diva	DVLV-600P	1	34	5%	98%	<1s	
Lutron	Lumina	LG-103P	1	77	0%	99%	>1s	8s Turn on Time at Low End Dimming
Lutron	Skylark	SLV-600P	1	34	5%	99%	<1s	
Lutron	Nova	NTLV-600	1	34	5%	100%	<1s	

Manufacturer	Series	Model	"Minimum Luminaires (per circuit)"	"Maximum Luminaires (per circuit)"	Minimum Measured Light Output	Maximum Measured Light Output	Low End Start Time	Additional Comments
EATON	Decorator	DAL06P	1	17	5%	100%	<1s	
EATON	Smart	AAL06P	1	17	5%	99%	<1s	
EATON	Toggle	TAL06P	1	17	5%	99%	<1s	
EATON	Slide	SAL06P	1	17	5%	100%	<1s	
EATON	Slide	SLC03P	1	17	5%	99%	<1s	
EATON	Toggle	DLC03P	1	17	5%	99%	<1s	
EATON	iLumin	SC277-06-UN	1	27	1%	100%	>1s	5s Turn on Time at Low End Dimming
Vantage	Enclosure Module	SDM12-EM	1	25	1%	95%	>1s	2s Start Time
Vantage	Enclosure Module	UDIMMOD-FWD	1	48	1%	95%	>1s	2s Start Time
Vantage	Enclosure Module	UDIMMOD-REV	1	48	1%	96%	>1s	2s Start Time
Vantage	ScenePoint	DS/RD	1	8	1%	96%	>1s	2s Start Time
Vantage	DIN Enclosure	LVRS8-DIN	1	40	1%	95%	>1s	2s Start Time
Crestron	iLux	CLS-EXP-DIM	--	--	1%	100%	--	
Crestron	iLux	CLS-EXP-DIMU	--	--	4%	100%	--	
Crestron	CLX	CLX-1DIM4	--	--	2%	100%	--	
Crestron	CLX	CLX-1DIM8	--	--	2%	100%	--	
Crestron	CLX	CLX-2DIM2	--	--	2%	100%	--	
Crestron	CLX	CLX-2DIM8	--	--	2%	100%	--	
Crestron	DIN Rail	DIN-1DIM4	--	--	3%	100%	--	
Crestron	DIN Rail	DIN-1DIMU4	--	--	9%	100%	--	
Crestron	Cameo Express	CLW-DIMEX-E	--	--	1%	100%	--	
Crestron	Cameo	CLW-DIMEX-P	--	--	1%	100%	--	
Crestron	Cameo Express	CLW-DIMSWEX-E	--	--	1%	100%	--	
Crestron	Cameo	CLW-DIMSWEX-P	--	--	1%	100%	--	
Crestron	Prodigy	P-DIMEX	--	--	1%	100%	--	
Crestron	Green Light	GLX-DIM6	--	--	2%	100%	--	
Crestron	Green Light Express	GLXX-2DIM8	--	--	2%	100%	--	
Crestron	Cameo Express	CLW-DELVEX-E	--	--	1%	100%	--	
Crestron	Cameo	CLW-DELVEX-P	--	--	1%	100%	--	
Crestron	CLX	CLX-1DIMU4	--	--	1%	100%	--	
Crestron	CLX	CLX-2DIMU8	--	--	1%	100%	--	
Lutron	Diva	C-L wall-mount dimmers (T1, T4, T5, T8)	1	8	17%	99%	<1s	
Lutron	Skylark	C-L wall-mount dimmers (T1, T4, T5, T8)	1	8	17%	99%	<1s	
Lutron	Skylark Contour	C-L wall-mount dimmers (T1, T4, T5, T8)	1	8	17%	99%	<1s	
Lutron	Ariadni / Toggler	C-L wall-mount dimmers (T1, T4, T5, T8)	1	8	17%	99%	<1s	
Lutron	Lumea	C-L wall-mount dimmers (T1, T4, T5, T8)	1	8	17%	99%	<1s	
Lutron	Maestro	MACL-153M	1	8	13%	93%	<1s	
Lutron	RadioRA 2	RRD-10ND	1	7	13%	98%	<1s	

Manufacturer	Series	Model	"Minimum Luminaires (per circuit)"	"Maximum Luminaires (per circuit)"	Minimum Measured Light Output	Maximum Measured Light Output	Low End Start Time	Additional Comments
Lutron	HomeWorks QS	HQRD-10ND	1	7	13%	98%	<1s	
Lutron	HomeWorks	HxD-6ND	1	3	20%	96%	<1s	
Lutron	Stanza	SZ-6ND	1	3	20%	96%	<1s	
Lutron	Panel Module	HW/LP-RPM-4A-120	1	16	16%	99%	>1s	
Lutron	Panel Module	HW/LP-RPM-4U-120	1	15	17%	99%	<1s	
Lutron	Grafik QS/Wallbox Power Module	"Grafik Eye QS Main Unit Family/ LQRJ-WPM-6P"	1	15	19%	99%	<1s	
Lutron	Panel Module	GP (Harrier) Card	1	15	19%	99%	<1s	
Lutron	150W C.L Wall Mount 3.0	DVCL-153P(T9)	1	8	17%	99%	<1s	
Lutron	Maestro Sensor	MSCL-OP153M(T2)	1	8	20%	92%	<1s	
Lutron	Maestro Sensor	MSCL-VP153M(T2)	1	8	20%	92%	<1s	
Lutron	Grafik Eye 3000/HomeWorks	Grafik Eye 3000 Family/HWI-WPM-6D-120	1	15	19%	99%	<1s	
Lutron	Caseta Wireless	PD-6WCL (SD11)	1	8	19%	95%	<1s	
Lutron	RadioRA 2	RRD-6CL (R3)	1	8	11%	96%	<1s	
Lutron	Maestro Wireless	MRF2-6CL (M6)	1	8	11%	96%	<1s	
Lutron	HomeWorks QS	HQRD-6CL (H2)	1	8	11%	96%	<1s	
Lutron	HomeWorks QS	HQRA-6CL (H2)	1	8	11%	96%	<1s	
Lutron	RadioRA 2	RRD-H6BRL (with neutral)	1	5	11%	99%	>1s	
Lutron	HomeWorks QS	HQRD-H6BRL (with neutral)	1	8	11%	99%	>1s	
Lutron	Diva	250W C.L dimmers (T5, T8)	1	12	17%	99%	<1s	
Lutron	Ariadni	250W C.L dimmers (T5, T8)	1	12	17%	99%	<1s	
Lutron	Nova T	NTCL-250 (T8)	1	12	17%	99%	<1s	
Lutron	HomeWorks QS/myRoom	LQSE-4A1-D	1	3	18%	99%	<1s	
Lutron	HomeWorks QS/myRoom	MQSE-4A1-D	1	3	18%	99%	<1s	
Lutron	HomeWorks QS/myRoom	MQSE-3A1	1	3	18%	99%	<1s	
Lutron	HomeWorks QS/myRoom	MQSE-2A1-D	1	3	18%	99%	<1s	
Lutron	Grafik T	GT-5NEM	1	13	18	99	<1s	
Lutron	Grafik T	GTJ-5NEM	1	13	18	99	<1s	

Manufacturer	Series	Model	"Minimum Luminaires (per circuit)"	"Maximum Luminaires (per circuit)"	Minimum Measured Light Output	Maximum Measured Light Output	Low End Start Time	Additional Comments
EATON	Toggle	TI061	1	34	2%	95%	<1s	
EATON	Aspire	9530AW	1	34	2%	100%	>1s	3s Turn on Time at Low End Dimming
EATON	Rotary	RI061	1	34	33%	98%	<1s	
EATON	SureSlide	SF8AP	1	54	7%	99%	<1s	
EATON	Decorator	DE06P	1	34	1%	97%	>1s	4s Turn on Time at Low End Dimming
Lutron	Toggler	TG-600P	1	34	5%	100%	<1s	
Lutron	Diva	DV-600P	1	34	0%	99%	>1s	6s Turn on Time at Low End Dimming
Lutron	Lumea	LG600P	1	34	1%	99%	>1s	4s Turn on Time at Low End Dimming
Lutron	Skylark	S-600P	1	34	1%	99%	>1s	6s Turn on Time at Low End Dimming
Lutron	Skylark Contour	CT103P	1	34	2%	99%	<1s	
Lutron	Diva	DV603P	1	34	2%	99%	>1s	3s Turn on Time at Low End Dimming
Lutron	Nova T	NTFTU-5A	1	34	11%	100%	<1s	
Lutron	Maestro	MAELV600	1	34	5%	100%	<1s	
Lutron	Faetra	FAELV500	1	28	4%	99%	<1s	
Lutron	Diva	DVELV303P	1	17	5%	91%	<1s	
Lutron	Skylark	SELV300P	1	17	6%	93%	<1s	
Leviton	SureSlide	6674	1	8	5%	100%	<1s	
Leviton	Illumatech	IPL06	1	8	5%	100%	<1s	
Leviton	Decora	6673	1	34	7%	100%	<1s	
Leviton	SureSlide	6631-2	1	34	5%	100%	<1s	
Leviton	Illumatech	IPI06	1	34	5%	100%	<1s	
Leviton	Vizia	VP106	1	34	4%	100%	<1s	
Leviton	SureSlide	6633-P	1	34	5%	100%	<1s	
Leviton	Acenti	ATX10	1	57	3%	100%	>1s	4s Turn on Time at Low End Dimming
Leviton	Vizia	VPE06	1	34	5%	100%	<1s	
Leviton	Illumatech	IPE04	1	17	4%	100%	<1s	
Leviton	Vizia	VZE04	1	22	5%	100%	<1s	
Legrand	Pass&Seymour Harmony	H703PTUW	1	25	3%	100%	<1s	
Legrand	Pass&Seymour Harmony	HLV703PTC	1	40	5%	100%	<1s	
Lutron	Ariadni	AY-600P	1	34	5%	99%	<1s	
Lutron	Contour	CT-103P	1	57	3%	99%	>1s	2s Turn on Time at Low End Dimming
Lutron	Contour	CT-600P	1	34	2%	100%	>1s	4s Turn on Time at Low End Dimming
Lutron	Rotary	D-600P	1	34	16%	100%	<1s	
Lutron	Diva	DV-600P	1	34	1%	100%	>1s	6s Turn on Time at Low End Dimming
Lutron	Glyder	GL-600P	1	34	2%	100%	>1s	7s Turn on Time at Low End Dimming

Manufacturer	Series	Model	"Minimum Luminaires (per circuit)"	"Maximum Luminaires (per circuit)"	Minimum Measured Light Output	Maximum Measured Light Output	Low End Start Time	Additional Comments
Lutron	Lumia	LG-600PH	1	34	1%	100%	>1s	7s Turn on Time at Low End Dimming
Lutron	Ariadni	AYLV-600P	1	25	6%	100%	<1s	
Lutron	Glyder	GLV-600	1	25	2%	100%	<1s	
Lutron	Diva	DVLV-600P	1	25	3%	100%	<1s	
Lutron	Lumina	LG-103P	1	57	5%	100%	<1s	
Lutron	Skylark	SLV-600P	1	25	2%	100%	>1s	3s Turn on Time at Low End Dimming
Lutron	Nova	NTLV-600	1	25	2%	100%	<1s	
Lutron	Nova	NT-600	1	34	0%	100%	>1s	7s Turn on Time at Low End Dimming

Manufacturer	Series	Model	"Minimum Luminaires (per circuit)"	"Maximum Luminaires (per circuit)"	Minimum Measured Light Output	Maximum Measured Light Output	Low End Start Time	Additional Comments
EATON	Decorator	DAL06P	1	11	5%	100%	<1s	
EATON	Smart	AAL06P	1	11	5%	99%	<1s	
EATON	Toggle	TAL06P	1	11	5%	100%	<1s	
EATON	Slide	SAL06P	1	11	5%	100%	<1s	
EATON	Slide	SLC03P	1	11	5%	100%	<1s	
EATON	Toggle	DLC03P	1	11	5%	100%	<1s	
EATON	iLumin	SC277-06-UN	1	18	2%	100%	<1s	Slight Flash On Start Up
Vantage	Enclosure Module	SDM12-EM	1	18	2%	95%	<1s	2s Start Time
Vantage	Enclosure Module	UDIMMOD-FWD	1	3	2%	95%	<1s	2s Start Time
Vantage	Enclosure Module	UDIMMOD-REV	1	34	2%	95%	<1s	2s Start Time
Vantage	ScenePoint	DS/RD	1	5	1%	95%	<1s	2s Start Time
Vantage	DIN Enclosure	LVRS8-DIN	1	28	3%	95%	<1s	2s Start Time
Crestron	iLux	CLS-C6	--	--	4%	100%	--	
Crestron	iLux	CLS-C6M	--	--	4%	100%	--	
Crestron	iLux	CLS-C6EX	--	--	4%	100%	--	
Crestron	iLux	CLS-C6MEX	--	--	4%	100%	--	
Crestron	iLux	CLS-C6MRF	--	--	4%	100%	--	
Crestron	iLux	CLS-C6RF	--	--	4%	100%	--	
Crestron	iLux	CLS-EXP-DIM	--	--	3%	100%	--	
Crestron	iLux	CLS-EXP-DIMU	--	--	5%	100%	--	
Crestron	CLX	CLX-1DIM4	--	--	5%	100%	--	
Crestron	CLX	CLX-1DIM8	--	--	5%	100%	--	
Crestron	CLX	CLX-2DIM2	--	--	5%	100%	--	
Crestron	CLX	CLX-2DIM8	--	--	5%	100%	--	
Crestron	DIN Rail	DIN-1DIM4	--	--	4%	100%	--	
Crestron	DIN Rail	DIN-1DIMU4	--	--	4%	100%	--	
Crestron	Cameo Express	CLW-DIMEX-E	--	--	3%	100%	--	
Crestron	Cameo	CLW-DIMEX-P	--	--	3%	100%	--	
Crestron	Cameo Express	CLW-DIMSWEX-E	--	--	3%	100%	--	
Crestron	Cameo	CLW-DIMSWEX-P	--	--	3%	100%	--	
Crestron	Prodigy	P-DIMEX	--	--	3%	100%	--	
Crestron	Green Light	GLX-DIM6	--	--	2%	100%	--	
Crestron	Green Light Express	GLXX-2DIM8	--	--	4%	100%	--	
Crestron	CLX	CLX-1DIMU4	--	--	1%	100%	--	
Crestron	CLX	CLX-2DIMU8	--	--	1%	100%	--	
Lutron	Diva	C-L wall-mount dimmers (T1, T4, T5, T8)	1	6	15%	99%	<1s	
Lutron	Skylark	C-L wall-mount dimmers (T1, T4, T5, T8)	1	6	15%	99%	<1s	
Lutron	Skylark Contour	C-L wall-mount dimmers (T1, T4, T5, T8)	1	6	15%	99%	<1s	
Lutron	Ariadni / Toggler	C-L wall-mount dimmers (T1, T4, T5, T8)	1	6	15%	99%	<1s	

Manufacturer	Series	Model	"Minimum Luminaires (per circuit)"	"Maximum Luminaires (per circuit)"	Minimum Measured Light Output	Maximum Measured Light Output	Low End Start Time	Additional Comments
Lutron	Lumea	C-L wall-mount dimmers (T1, T4, T5, T8)	1	6	15%	99%	<1s	
Lutron	Maestro	MACL-153M	1	6	18%	93%	<1s	
Lutron	RadioRA 2	RRD-10ND	1	6	17%	98%	<1s	
Lutron	HomeWorks QS	HQRD-10ND	1	6	17%	98%	<1s	
Lutron	Panel Module	HW/LP-RPM-4A-120	1	13	20%	99%	<1s	
Lutron	Panel Module	HW/LP-RPM-4U-120	1	12	19%	100%	<1s	
Lutron	Grafik QS/Wallbox Power Module	"Grafik Eye QS Main Unit Family/ LQRJ-WPM-6P"	1	12	15%	99%	<1s	
Lutron	Panel Module	GP (Harrier) Card	1	12	17%	99%	<1s	
Lutron	Maestro Sensor	MSCL-OP153M(T2)	1	6	17%	94%	<1s	
Lutron	Maestro Sensor	MSCL-VP153M(T2)	1	6	17%	94%	<1s	
Lutron	Grafik Eye 3000/HomeWorks	Grafik Eye 3000 Family/HWI-WPM-6D-120	1	12	15%	99%	<1s	
Lutron	Caseta Wireless	PD-6WCL (SD11)	1	6	16%	95%	<1s	
Lutron	RadioRA 2	RRD-6CL (R3)	1	6	15%	97%	<1s	
Lutron	Maestro Wireless	MRF2-6CL (M6)	1	6	15%	97%	<1s	
Lutron	HomeWorks QS	HQRD-6CL (H2)	1	6	15%	97%	<1s	
Lutron	HomeWorks QS	HQRA-6CL (H2)	1	6	15%	97%	<1s	
Lutron	RadioRA 2	RRD-H6BRL (with neutral)	1	4	15%	97%	<1s	
Lutron	HomeWorks QS	HQRD-H6BRL (with neutral)	1	4	15%	97%	<1s	
Lutron	Diva	250W C-L dimmers (T5, T8)	1	10	15%	99%	<1s	
Lutron	Ariadni	250W C-L dimmers (T5, T8)	1	10	15%	99%	<1s	
Lutron	Nova T	NTCL-250 (T8)	1	10	15%	99%	<1s	
Lutron	Grafik T	GT-150 (T6) (without neutral)	1	6	15%	99%	<1s	
Lutron	Grafik T	GTJ-150 (M6) (without neutral)	1	6	15%	99%	<1s	
Lutron	HomeWorks QS/myRoom	LQSE-4A1-D	1	3	16%	99%	<1s	
Lutron	HomeWorks QS/myRoom	MQSE-4A1-D	1	3	16%	99%	<1s	
Lutron	HomeWorks QS/myRoom	MQSE-3A1	1	3	16%	99%	<1s	
Lutron	HomeWorks QS/myRoom	MQSE-2A1-D	1	3	16%	99%	<1s	
Lutron	Grafik T	5NEM	1	10	18	99	<1s	
Lutron	Grafik T	GTJ-5NEM	1	10	18	99	<1s	

Manufacturer	Series	Model	"Minimum Luminaires (per circuit)"	"Maximum Luminaires (per circuit)"	Minimum Measured Light Output	Maximum Measured Light Output	Low End Start Time	Additional Comments
EATON	Toggle	TI061	1	23	5%	96%	<1s	
EATON	Aspire	9530AW	1	23	4%	100%	<1s	
EATON	Rotary	RI061	1	23	32%	100%	<1s	
EATON	Decorator	DE06P	1	23	4%	98%	<1s	
EATON	SureSlide	SF8AP	1	36	19%	100%	<1s	
Lutron	Toggler	TG-600P	1	23	7%	99%	<1s	
Lutron	Diva	DV-600P	1	23	5%	99%	<1s	
Lutron	Maestro	MAW600	1	23	2%	99%	<1s	Slight Flicker
Lutron	Skylark	S-600P	1	23	3%	99%	<1s	
Lutron	Skylark Contour	CT103P	1	38	5%	99%	<1s	
Lutron	Diva	DV603P	1	23	4%	99%	>1s	4 Seconds Start Time for Low End Dimming
Lutron	Nova T	NTFTU-5A	1	22	17%	100%	<1s	
Lutron	Maestro	MAELV600	1	23	5%	99%	<1s	
Lutron	Faetra	FAELV500	1	19	5%	99%	<1s	
Lutron	Diva	DVELV303P	1	11	5%	95%	<1s	
Lutron	Skylark	SELV300P	1	11	5%	96%	<1s	
Leviton	SureSlide	6674	1	5	5%	99%	<1s	
Leviton	Illumatech	IPL06	1	5	5%	99%	<1s	Slight Shimmer
Leviton	Decora	6673	1	23	7%	99%	<1s	
Leviton	Illumatech	IPI06	1	23	5%	100%	<1s	
Leviton	Vizia	VP106	1	23	4%	99%	<1s	Slight Shimmer
Leviton	SureSlide	6633-P	1	19	5%	100%	<1s	
Leviton	Acenti	ATX10	1	38	4%	99%	<1s	Slight Shimmer
Leviton	Vizia	VPE06	1	23	5%	100%	<1s	
Leviton	Illumatech	IPE04	1	11	5%	100%	<1s	
Leviton	Vizia	VZE04	1	15	5%	100%	<1s	
Legrand	Pass&Seymour Harmony	H703PTUW	1	17	5%	100%	<1s	
Legrand	Pass&Seymour Harmony	HLV703PTC	1	26	5%	100%	<1s	
Hubbell	TradeSelect	RD600PDK	1	23	13%	99%	<1s	
Lutron	Ariadni	AY-600P	1	23	8%	99%	<1s	
Lutron	Contour	CT-103P	1	38	5%	100%	<1s	
Lutron	Contour	CT-600P	1	23	3%	100%	>1s	4 Seconds Start Time for Low End Dimming
Lutron	Diva	DV-600P	1	23	2%	100%	>1s	4 Seconds Start Time for Low End Dimming
Lutron	Glyder	GL-600P	1	23	4%	100%	<1s	
Lutron	Lumia	LG-600PH	1	23	2%	100%	>1s	4 Seconds Start Time for Low End Dimming
Lutron	Maestro	MA600	1	23	3%	100%	<1s	Slight Flicker
Lutron	Nova	N-600	1	23	1%	100%	>1s	3 Seconds Start Time for Low End Dimming
Lutron	Skylark	S-600P	1	23	1%	100%	>1s	5 Seconds Start Time for Low End Dimming

Manufacturer	Series	Model	"Minimum Luminaires (per circuit)"	"Maximum Luminaires (per circuit)"	Minimum Measured Light Output	Maximum Measured Light Output	Low End Start Time	Additional Comments
Lutron	Centurion	C-600P	1	23	1%	100%	>1s	3 Seconds Start Time for Low End Dimming
Lutron	Ariadni	AYLV-600P	1	17	9%	100%	<1s	
Lutron	Glyder	GLV-600	1	17	4%	100%	<1s	
Lutron	Diva	DVLV-600P	1	17	5%	100%	<1s	
Lutron	Lumina	LG-103P	1	38	8%	100%	<1s	
Lutron	Skylark	SLV-600P	1	17	4%	100%	>1s	2 Seconds Start Time for Low End Dimming
Lutron	Nova	NTLV-600	1	17	4%	100%	<1s	
Lutron	Nova	NT-600	1	23	1%	100%	>1s	2 Seconds Start Time for Low End Dimming

Manufacturer	Series	Model	"Minimum Luminaires (per circuit)"	"Maximum Luminaires (per circuit)"	Minimum Measured Light Output	Maximum Measured Light Output	Low End Start Time	Additional Comments
EATON	Decorator	DAL06P	1	8	5%	100%	<1s	
EATON	Smart	AAL06P	1	8	5%	98%	<1s	
EATON	Toggle	TAL06P	1	8	5%	99%	<1s	
EATON	Slide	SAL06P	1	8	5%	99%	<1s	
EATON	Slide	SLC03P	1	8	5%	98%	<1s	
EATON	Toggle	DLC03P	1	8	5%	99%	<1s	
EATON	iLumin	SC277-06-UN	1	13	4%	100%	<1s	Slight Shimmer
Vantage	Enclosure Module	SDM12-EM	1	13	2%	95%	<1s	2s Start Time
Vantage	Enclosure Module	UDIMMOD-FWD	1	24	2%	96%	<1s	2s Start Time
Vantage	Enclosure Module	UDIMMOD-REV	1	24	2%	95%	<1s	2s Start Time
Vantage	ScenePoint	DS/RD	1	4	2%	95%	<1s	2s Start Time
Vantage	DIN Enclosure	LVRS8-DIN	1	20	7%	95%	<1s	2s Start Time
Crestron	iLux	CLS-C6	--	--	4%	100%	--	
Crestron	iLux	CLS-C6M	--	--	4%	100%	--	
Crestron	iLux	CLS-C6EX	--	--	4%	100%	--	
Crestron	iLux	CLS-C6MEX	--	--	4%	100%	--	
Crestron	iLux	CLS-C6MRF	--	--	4%	100%	--	
Crestron	iLux	CLS-C6RF	--	--	4%	100%	--	
Crestron	iLux	CLS-EXP-DIM	--	--	3%	100%	--	
Crestron	iLux	CLS-EXP-DIMU	--	--	6%	100%	--	
Crestron	CLX	CLX-1DIM4	--	--	5%	100%	--	
Crestron	CLX	CLX-1DIM8	--	--	5%	100%	--	
Crestron	CLX	CLX-2DIM2	--	--	5%	100%	--	
Crestron	CLX	CLX-2DIM8	--	--	5%	100%	--	
Crestron	DIN Rail	DIN-1DIM4	--	--	3%	100%	--	
Crestron	DIN Rail	DIN-1DIMU4	--	--	5%	100%	--	
Crestron	Cameo Express	CLW-DIMEX-E	--	--	3%	100%	--	
Crestron	Cameo	CLW-DIMEX-P	--	--	3%	100%	--	
Crestron	Cameo Express	CLW-DIMSWEX-E	--	--	3%	100%	--	
Crestron	Cameo	CLW-DIMSWEX-P	--	--	3%	100%	--	
Crestron	Prodigy	P-DIMEX	--	--	3%	100%	--	
Crestron	Green Light	GLX-DIM6	--	--	2%	100%	--	
Crestron	Green Light Express	GLXX-2DIM8	--	--	5%	100%	--	
Crestron	Cameo Express	CLW-DELVEX-E	--	--	3%	100%	--	
Crestron	Cameo	CLW-DELVEX-P	--	--	3%	100%	--	
Crestron	CLX	CLX-1DIMU4	--	--	2%	100%	--	
Crestron	CLX	CLX-2DIMU8	--	--	2%	100%	--	
Lutron	Diva	C-L wall-mount dimmers (T1, T4, T5, T8)	1	4	15%	99%	<1s	
Lutron	Skylark	C-L wall-mount dimmers (T1, T4, T5, T8)	1	4	15%	99%	<1s	

Manufacturer	Series	Model	"Minimum Luminaires (per circuit)"	"Maximum Luminaires (per circuit)"	Minimum Measured Light Output	Maximum Measured Light Output	Low End Start Time	Additional Comments
Lutron	Skylark Contour	C-L wall-mount dimmers (T1, T4, T5, T8)	1	4	15%	99%	<1s	
Lutron	Ariadni / Toggler	C-L wall-mount dimmers (T1, T4, T5, T8)	1	4	15%	99%	<1s	
Lutron	Lumea	C-L wall-mount dimmers (T1, T4, T5, T8)	1	4	15%	99%	<1s	
Lutron	Maestro	MACL-153M	1	4	9%	94%	<1s	
Lutron	RadioRA 2	RRD-10ND	1	3	12%	99%	<1s	
Lutron	HomeWorks QS	HQRD-10ND	1	3	12%	99%	<1s	
Lutron	HomeWorks	HxD-6ND	1	2	14%	98%	<1s	
Lutron	Stanza	SZ-6ND	1	2	14%	98%	<1s	
Lutron	Panel Module	HW/LP-RPM-4U-120	1	9	15%	99%	<1s	
Lutron	Grafik QS/Wallbox Power Module	"Grafik Eye QS Main Unit Family/ LQRJ-WPM-6P"	1	9	15%	99%	<1s	
Lutron	Panel Module	GP (Harrier) Card	1	9	16%	99%	<1s	
Lutron	Maestro Sensor	MSCL-OP153M(T2)	1	4	13%	96%	<1s	
Lutron	Maestro Sensor	MSCL-VP153M(T2)	1	4	13%	96%	<1s	
Lutron	Grafik Eye 3000/HomeWorks	Grafik Eye 3000 Family/HWI-WPM-6D-120	1	9	15%	99%	<1s	
Lutron	Caseta Wireless	PD-6WCL (SD11)	1	4	10%	97%	<1s	
Lutron	RadioRA 2	RRD-6CL (R3)	1	4	13%	97%	<1s	
Lutron	Maestro Wireless	MRF2-6CL (M6)	1	4	13%	97%	<1s	
Lutron	HomeWorks QS	HQRD-6CL (H2)	1	4	13%	97%	<1s	
Lutron	HomeWorks QS	HQRA-6CL (H2)	1	4	13%	97%	<1s	
Lutron	RadioRA 2	RRD-H6BRL (with neutral)	1	3	15%	99%	>1s	
Lutron	HomeWorks QS	HQRD-H6BRL (with neutral)	1	3	15%	99%	>1s	
Lutron	Diva	250W C-L dimmers (T5, T8)	1	6	15%	99%	<1s	
Lutron	Ariadni	250W C-L dimmers (T5, T8)	1	6	15%	99%	<1s	
Lutron	Nova T	NTCL-250 (T8)	1	6	15%	99%	<1s	
Lutron	HomeWorks QS/myRoom	LQSE-4A1-D	1	1	13%	99%	<1s	
Lutron	HomeWorks QS/myRoom	MQSE-4A1-D	1	1	13%	99%	<1s	
Lutron	HomeWorks QS/myRoom	MQSE-3A1	1	1	13%	99%	<1s	
Lutron	HomeWorks QS/myRoom	MQSE-2A1-D	1	1	13%	99%	<1s	

Manufacturer	Series	Model	"Minimum Luminaires (per circuit)"	"Maximum Luminaires (per circuit)"	Minimum Measured Light Output	Maximum Measured Light Output	Low End Start Time	Additional Comments
EATON	Toggle	TI061	1	16	6%	95%	<1s	
EATON	Aspire	9530AW	1	16	6%	100%	<1s	
EATON	Rotary	RI061	1	16	36%	99%	<1s	
EATON	SureSlide	SF8AP	1	27	22%	97%	<1s	
EATON	Decorator	DE06P	1	16	5%	94%	<1s	
Lutron	Toggler	TG-600P	1	16	8%	97%	<1s	
Lutron	Maestro	MAW600	1	16	1%	97	<1s	Slight Shimmer
Lutron	Skylark	S-600P	1	16	4%	98%	>1s	3 Seconds Turn On Time at Low End Dimming
Lutron	Skylark Contour	CT103P	1	28	7%	98%	<1s	
Lutron	Nova T	NTFTU-5A	1	16	19%	98%	<1s	
Lutron	Maestro	MAELV600	1	16	0%	98%	<1s	
Lutron	Faetra	FAELV500	1	14	0%	98%	<1s	
Lutron	Diva	DVELV303P	1	8	5%	93%	<1s	
Lutron	Skylark	SELV300P	1	8	5%	94%	<1s	
Leviton	SureSlide	6674	1	4	5%	97%	<1s	
Leviton	Illumatech	IPL06	1	4	5%	97%	<1s	
Leviton	Decora	6673	1	16	7%	97%	<1s	
Leviton	SureSlide	6631-2	1	16	2%	98%	>1s	3 Seconds Turn On Time at Low End Dimming
Leviton	Vizia	VP106	1	16	4%	98%	<1s	
Leviton	Acenti	ATX10	1	16	8%	98%	>1s	Slight Shimmer
Leviton	Plig in lamp Dimmer	TB103	1	8	2%	100%	<1s	
Leviton	Vizia	VPE06	1	16	5%	99%	<1s	
Leviton	Illumatech	IPE04	1	8	5%	99%	<1s	
Leviton	Vizia	VZE04	1	11	5%	98%	<1s	4 Seconds Turn On Time at Low End Dimming
Legrand	Pass&Seymour Harmony	H703PTUW	1	12	4%	98%	<1s	
Legrand	Pass&Seymour Harmony	HLV703PTC	1	19	5%	97%	>1s	
Hubbell	TradeSelect	RD600PDK	1	16	19%	97%	<1s	
Lutron	Ariadni	AY-600P	1	16	9%	99%	<1s	
Lutron	Contour	CT-103P	1	28	7%	98%	<1s	
Lutron	Contour	CT-600P	1	16	4%	99%	>1s	4 Seconds Turn On Time at Low End Dimming
Lutron	Rotary	D-600P	1	16	14%	98%	>1s	4 Seconds Turn On Time at Low End Dimming
Lutron	Diva	DV-600P	1	16	3%	98%	>1s	5 Seconds Turn On Time at Low End Dimming

Manufacturer	Series	Model	"Minimum Luminaires (per circuit)"	"Maximum Luminaires (per circuit)"	Minimum Measured Light Output	Maximum Measured Light Output	Low End Start Time	Additional Comments
Lutron	Glyder	GL-600P	1	16	4%	98%	>1s	3 Seconds Turn On Time at Low End Dimming
Lutron	Lumia	LG-600PH	1	16	3%	98%	<1s	5 Seconds Turn On Time at Low End Dimming
Lutron	Nova	N-600	1	16	1%	98%	<1s	
Lutron	Ariadni	AYLV-600P	1	12	10%	98%	<1s	
Lutron	Glyder	GLV-600	1	12	4%	99%	<1s	
Lutron	Diva	DVLV-600P	1	12	6%	98%	<1s	
Lutron	Lumina	LG-103P	1	28	10%	98%	<1s	
Lutron	Skylark	SLV-600P	1	12	4%	99%	>1s	2 Seconds Turn On Time at Low End Dimming
Lutron	Nova	NTLV-600	1	12	5%	99%	<1s	
Lutron	Nova	NT-600	1	16	2%	99%	>1s	2 Seconds Turn On Time at Low End Dimming

Manufacturer	Series	Model	"Minimum Luminaires (per circuit)"	"Maximum Luminaires (per circuit)"	Minimum Measured Light Output	Maximum Measured Light Output	Low End Start Time	Additional Comments
EATON	Decorator	DAL06P	1	5	5%	100%	<1s	
EATON	Smart	AAL06P	1	5	5%	99%	<1s	
EATON	Toggle	TAL06P	1	5	5%	100%	<1s	
EATON	Slide	SAL06P	1	5	5%	100%	<1s	
EATON	Slide	SLC03P	1	5	5%	99%	<1s	
EATON	Toggle	DLC03P	1	5	5%	99%	<1s	
EATON	iLumin	SC277-06-UN	1	8	5%	100%	<1s	
Vantage	Enclosure Module	SDM12-EM	1	9	2%	95%	<1s	2s Start Time
Vantage	Enclosure Module	UDIMMOD-FWD	1	18	2%	95%	<1s	2s Start Time
Vantage	Enclosure Module	UDIMMOD-REV	1	18	2%	96%	<1s	2s Start Time
Vantage	ScenePoint	DS/RD	1	3	1%	96%	<1s	2s Start Time
Vantage	DIN Enclosure	LVRS8-DIN	1	15	4%	95%	<1s	2s Start Time
Crestron	iLux	CLS-C6	--	--	2%	100%	--	
Crestron	iLux	CLS-C6M	--	--	2%	100%	--	
Crestron	iLux	CLS-C6EX	--	--	2%	100%	--	
Crestron	iLux	CLS-C6MEX	--	--	2%	100%	--	
Crestron	iLux	CLS-C6MRF	--	--	2%	100%	--	
Crestron	iLux	CLS-C6RF	--	--	2%	100%	--	
Crestron	iLux	CLS-EXP-DIM	--	--	2%	100%	--	
Crestron	iLux	CLS-EXP-DIMU	--	--	2%	100%	--	
Crestron	CLX	CLX-1DIM4	--	--	3%	100%	--	
Crestron	CLX	CLX-1DIM8	--	--	3%	100%	--	
Crestron	CLX	CLX-2DIM2	--	--	3%	100%	--	
Crestron	CLX	CLX-2DIM8	--	--	3%	100%	--	
Crestron	DIN Rail	DIN-1DIM4	--	--	2%	100%	--	
Crestron	DIN Rail	DIN-1DIMU4	--	--	3%	100%	--	
Crestron	Cameo Express	CLW-DIMEX-E	--	--	3%	100%	--	
Crestron	Cameo	CLW-DIMEX-P	--	--	3%	100%	--	
Crestron	Cameo Express	CLW-DIMSWEX-E	--	--	3%	100%	--	
Crestron	Cameo	CLW-DIMSWEX-P	--	--	3%	100%	--	
Crestron	Prodigy	P-DIMEX	--	--	3%	100%	--	
Crestron	Green Light	GLX-DIM6	--	--	1%	100%	--	
Crestron	Green Light Express	GLXX-2DIM8	--	--	4%	100%	--	
Crestron	Cameo Express	CLW-DELVEX-E	--	--	2%	100%	--	
Crestron	Cameo	CLW-DELVEX-P	--	--	2%	100%	--	
Crestron	CLX	CLX-1DIMU4	--	--	2%	100%	--	
Crestron	CLX	CLX-2DIMU8	--	--	2%	100%	--	
Lutron	Diva	C-L wall-mount dimmers (T1, T4, T5, T8)	1	3	6%	99%	<1s	
Lutron	Skylark	C-L wall-mount dimmers (T1, T4, T5, T8)	1	3	6%	99%	<1s	
Lutron	Skylark Contour	C-L wall-mount dimmers (T1, T4, T5, T8)	1	3	6%	99%	<1s	

Manufacturer	Series	Model	"Minimum Luminaires (per circuit)"	"Maximum Luminaires (per circuit)"	Minimum Measured Light Output	Maximum Measured Light Output	Low End Start Time	Additional Comments
Lutron	Ariadni / Toggler	C-L wall-mount dimmers (T1, T4, T5, T8)	1	3	6%	99%	<1s	
Lutron	Lumea	C-L wall-mount dimmers (T1, T4, T5, T8)	1	3	6%	99%	<1s	
Lutron	Maestro	MACL-153M	1	3	5%	96%	<1s	
Lutron	RadioRA 2	RRD-10ND	1	3	5%	99%	<1s	
Lutron	Maestro Wireless	MRF2-6ND	1	2	5%	99%	<1s	
Lutron	HomeWorks QS	HQRD-6ND	1	2	5%	99%	<1s	
Lutron	HomeWorks QS	HQRD-10ND	1	3	5%	99%	<1s	
Lutron	HomeWorks	HxD-6ND	1	2	11%	99%	<1s	
Lutron	Stanza	SZ-6ND	1	2	11%	99%	<1s	
Lutron	Panel Module	HW/LP-RPM-4U-120	1	10	11%	98%	<1s	
Lutron	Grafik QS/Wallbox Power Module	"Grafik Eye QS Main Unit Family/ LQRJ-WPM-6P"	1	10	10%	99%	<1s	
Lutron	Panel Module	GP (Harrier) Card	1	10	7%	99%	<1s	
Lutron	Maestro Sensor	MSCL-OP153M(T2)	1	3	6%	97%	<1s	
Lutron	Maestro Sensor	MSCL-VP153M(T2)	1	3	6%	97%	<1s	
Lutron	Grafik Eye 3000/HomeWorks	Grafik Eye 3000 Family/HWI-WPM-6D-120	1	10	10%	99%	<1s	
Lutron	Caseta Wireless	PD-6WCL (SD11)	1	3	7%	98%	<1s	
Lutron	RadioRA 2	RRD-6CL (R3)	1	3	8%	98%	<1s	
Lutron	Maestro Wireless	MRF2-6CL (M6)	1	3	8%	98%	<1s	
Lutron	HomeWorks QS	HQRD-6CL (H2)	1	3	8%	98%	<1s	
Lutron	HomeWorks QS	HQRA-6CL (H2)	1	3	8%	98%	<1s	
Lutron	RadioRA 2	RRD-H6BRL (with neutral)	1	2	5%	98%	<1s	
Lutron	HomeWorks QS	HQRD-H6BRL (with neutral)	1	2	5%	98%	<1s	
Lutron	Diva	250W C-L dimmers (T5, T8)	1	5	6%	99%	<1s	
Lutron	Ariadni	250W C-L dimmers (T5, T8)	1	5	6%	99%	<1s	
Lutron	Nova T	NTCL-250 (T8)	1	5	6%	99%	<1s	
Lutron	Grafik T	GT-150 (T6) (without neutral)	1	3	8%	99%	<1s	
Lutron	Grafik T	GTJ-150 (M6) (without neutral)	1	3	8%	99%	<1s	
Lutron	HomeWorks QS/myRoom	LQSE-4A1-D	1	2	6%	99%	<1s	
Lutron	HomeWorks QS/myRoom	MQSE-4A1-D	1	2	6%	99%	<1s	
Lutron	HomeWorks QS/myRoom	MQSE-3A1	1	2	6%	99%	<1s	
Lutron	HomeWorks QS/myRoom	MQSE-2A1-D	1	2	6%	99%	<1s	
Lutron	Caseta Wireless	PD-10NXD(SD11)	1	4	7%	98%	<1s	

Manufacturer	Series	Model	"Minimum Luminaires (per circuit)"	"Maximum Luminaires (per circuit)"	Minimum Measured Light Output	Maximum Measured Light Output	Low End Start Time	Additional Comments
EATON	Toggle	TI061	1	11	6%	96%	<1s	
EATON	Aspire	9530AW	1	11	6%	100%	<1s	
EATON	Rotary	RI061	1	11	36%	100%	<1s	
Eaton	Slide	SF8AP	1	17	5%	100%	<1s	Slight Flicker
EATON	Decorator	DE06P	1	11	5%	97%	<1s	
Lutron	Toggler	TG-600P	1	11	10%	100%	<1s	
Lutron	Diva	DV-600P	1	11	4%	98%	<1s	
Lutron	Maestro	MAW600	1	11	1%	100%	<1	
Lutron	Lumea	LG600P	1	11	4%	98%	<1s	
Lutron	Skylark	S-600P	1	11	4%	98%	<1s	
Lutron	Skylark Contour	CT103P	1	18	6%	98%	<1s	
Lutron	Diva	DV603P	1	11	6%	98%	<1s	
Lutron	Nova T	NTFTU-5A	1	11	20%	100%	<1s	
Lutron	Maestro	MAELV600	1	11	1%	100%	<1s	
Lutron	Faedra	FAELV500	1	9	1%	100%	<1s	
Lutron	Diva	DVELV303P	1	5	5%	98%	<1s	
Lutron	Skylark	SELV300P	1	5	5%	97%	<1s	
Leviton	SureSlide	6674	1	2	5%	99%	<1s	
Leviton	Illumatech	IPL06	1	2	5%	99%	<1s	
Leviton	Decora	6673	1	11	7%	99%	<1s	
Leviton	SureSlide	6631-2	1	11	2%	99%	<1s	
Leviton	Illumatech	IPI06	1	11	5%	100%	<1s	
Leviton	Vizia	VP106	1	11	5%	100%	<1s	Slight Shimmer
Leviton	Decora	6161	1	9	7%	99%	<1s	
Leviton	Acenti	ATX10	1	18	6%	100%	>1s	
Leviton	Plug In Lamp Dimmer	TBI03	1	5	3%	100%	>1s	
Leviton	Vizia	VPE06	1	11	5%	100%	<1s	
Leviton	Illumatech	IPE04	1	5	5%	100%	<1s	
Leviton	Vizia	VZE04	1	7	4%	100%	<1s	
Legrand	Pass&Seymour Harmony	H703PTUW	1	8	4%	100%	<1s	
Legrand	Pass&Seymour Harmony	HLV703PTC	1	11	5%	100%	<1s	
Hubbell	TradeSelect	RD600PDK	1	13	19%	99%	<1s	
Lutron	Ariadni	AY-600P	1	11	9%	99%	<1s	
Lutron	Contour	CT-103P	1	18	6%	98%	<1s	
Lutron	Contour	CT-600P	1	11	4%	98%	<1s	
Lutron	Diva	DV-600P	1	11	3%	99%	<1s	
Lutron	Glyder	GL-600P	1	11	4%	99%	<1s	
Lutron	Lumia	LG-600PH	1	11	2%	99%	>1s	2s Start Time at Low End Dimming
Lutron	Maestro	MA600	1	11	1%	96%	<1s	
Lutron	Nova	N-600	1	11	1%	97%	<1s	

Manufacturer	Series	Model	"Minimum Luminaires (per circuit)"	"Maximum Luminaires (per circuit)"	Minimum Measured Light Output	Maximum Measured Light Output	Low End Start Time	Additional Comments
Lutron	Skylark	S-600P	1	11	2%	98%	>1s	3s Start Time at Low End Dimming
Lutron	Centurion	C-600P	1	11	2%	99%	>1s	2s Start Time at Low End Dimming
Lutron	Ariadni	AYLV-600P	1	8	10%	99%	<1s	
Lutron	Glyder	GLV-600	1	8	4%	99%	<1s	
Lutron	Diva	DVLV-600P	1	8	6%	99%	<1s	
Lutron	Lumina	LG-103P	1	18	9%	98%	<1s	
Lutron	Skylark	SLV-600P	1	8	5%	98%	<1s	
Lutron	Nova	NTLV-600	1	8	5%	99%	<1s	
Lutron	Nova	NT-600	1	11	2%	99%	<1s	

1000 Lumens / 250mA / DE010

Dimmer Make	Dimmer Series	Dimmer Model #	Types of Dimmer	Minimum Lamps or Luminaires (per circuit)	Maximum Recommended Luminaires (per circuit) at 120V	Maximum Recommended Luminaires (per circuit) at 277V	Max Dimming percentage (%)	Min Dimming percentage (%)	Low End Start Time
Eaton	Slide Dimmer	SF10P	0-10v	1	86	100	100	0	NA
Eaton	Decorator Dimmer	DF10P	0-10v	1	86	100	100	0	NA
Leviton	Illumatech	IP710-DL	0-10v	1	48	48	100	0	NA
Lutron	NTFTV	NOVA T	0-10v	1	51	51	100	0	NA
Lutron	DIVA	DVTV	0-10v	1	56	56	100	0	NA
Eaton	iLumin	SC277-06	0-10v	1	134	158	96	0	NA
Eaton	Greengate	CK4A	0-10v	1	158	158	100	0	NA

1500 Lumens / 350mA / DE010

Dimmer Make	Dimmer Series	Dimmer Model #	Types of Dimmer	Minimum Lamps or Luminaires (per circuit)	Maximum Recommended Luminaires (per circuit) at 120V	Maximum Recommended Luminaires (per circuit) at 277V	Max Dimming percentage (%)	Min Dimming percentage (%)	Low End Start Time
Eaton	Slide Dimmer	SF10P	0-10v	1	62	77	100	0	NA
Eaton	Decorator Dimmer	DF10P	0-10v	1	62	77	100	0	NA
Leviton	Illumatech	IP710-DL	0-10v	1	48	48	100	0	NA
Lutron	NTFTV	NOVA T	0-10v	1	52	52	100	0	NA
Lutron	DIVA	DVTV	0-10v	1	51	51	100	0	NA
Eaton	iLumin	SC277-06	0-10v	1	98	158	98	0	NA
Eaton	Greengate	CK4A	0-10v	1	123	158	100	0	NA

2000 Lumens / 500mA / DE010

Dimmer Make	Dimmer Series	Dimmer Model #	Types of Dimmer	Minimum Lamps or Luminaires (per circuit)	Maximum Recommended Luminaires (per circuit) at 120V	Maximum Recommended Luminaires (per circuit) at 277V	Max Dimming percentage (%)	Min Dimming percentage (%)	Low End Start Time
Eaton	Slide Dimmer	SF10P	0-10v	1	43	57	100	0	NA
Eaton	Decorator Dimmer	DF10P	0-10v	1	43	57	100	0	NA
Leviton	Illumatech	IP710-DL	0-10v	1	43	48	100	0	NA
Lutron	NTFTV	NOVA T	0-10v	1	52	52	100	0	NA
Lutron	DIVA	DVTV	0-10v	1	51	51	100	0	NA
Eaton	iLumin	SC277-06	0-10v	1	71	139	96	0	NA
Eaton	Greengate	CK4A	0-10v	1	86	158	100	0	NA

3000 Lumens / 700mA / DE010

Dimmer Make	Dimmer Series	Dimmer Model #	Types of Dimmer	Minimum Lamps or Luminaires (per circuit)	Maximum Recommended Luminaires (per circuit) at 120V	Maximum Recommended Luminaires (per circuit) at 277V	Max Dimming percentage (%)	Min Dimming percentage (%)	Low End Start Time
Eaton	Slide Dimmer	SF10P	0-10v	1	34	46	100	1	<1S
Eaton	Decorator Dimmer	DF10P	0-10v	1	34	46	100	1	<1S
Leviton	Illuminatech	IP710-DL	0-10v	1	34	42	100	1	<1S
Lutron	NTFTV	NOVA T	0-10v	1	54	71	100	1	<1S
Lutron	DIVA	DVTV	0-10v	1	54	69	96	1	<1S
Eaton	iLumin	SC277-06	0-10v	1	54	110	98	0	NA
Eaton	Greengate	CK4A	0-10v	1	67	137	100	0	NA

4000 Lumens / 1050mA / DE010

Dimmer Make	Dimmer Series	Dimmer Model #	Types of Dimmer	Minimum Lamps or Luminaires (per circuit)	Maximum Recommended Luminaires (per circuit) at 120V	Maximum Recommended Luminaires (per circuit) at 277V	Max Dimming percentage (%)	Min Dimming percentage (%)	Low End Start Time
Eaton	Slide Dimmer	SF10P	0-10v	1	22	31	100	1%	<1S
Eaton	Decorator Dimmer	DF10P	0-10v	1	22	31	100	1%	<1S
Leviton	Illuminatech	IP710-DL	0-10v	1	22	28	97	1%	<1S
Lutron	NTFTV	NOVA T	0-10v	1	35	69	100	1%	<1S
Lutron	DIVA	DVTV	0-10v	1	35	69	100	1%	<1S
Eaton	iLumin	SC277-06	0-10v	1	35	78	98	NA	NA
Eaton	Greengate	CK4A	0-10v	1	44	98	100	NA	NA

5000 Lumens / 1400mA / DE010

Dimmer Make	Dimmer Series	Dimmer Model #	Types of Dimmer	Minimum Lamps or Luminaires (per circuit)	Maximum Recommended Luminaires (per circuit) at 120V	Maximum Recommended Luminaires (per circuit) at 277V	Max Dimming percentage (%)	Min Dimming percentage (%)	Low End Start Time
Eaton	Slide Dimmer	SF10P	0-10v	1	16	23	100	1	>1S
Eaton	Decorator Dimmer	DF10P	0-10v	1	16	23	100	1	>1S
Leviton	Illuminatech	IP710-DL	0-10v	1	16	20	100	1	>1S
Lutron	NTFTV	NOVA T	0-10v	1	26	58	100	1	>1S
Lutron	DIVA	DVTV	0-10v	1	26	58	100	1	>1S
Eaton	iLumin	SC277-06	0-10v	1	26	58	100	1	>1S
Eaton	Greengate	CK4A	0-10v	1	32	72	100	1	>1S

6000 Lumens / 1400mA / DE010

Dimmer Make	Dimmer Series	Dimmer Model #	Types of Dimmer	Minimum Lamps or Luminaires (per circuit)	Maximum Recommended Luminaires (per circuit) at 120V	Maximum Recommended Luminaires (per circuit) at 277V	Max Dimming percentage (%)	Min Dimming percentage (%)	Low End Start Time
Eaton	Slide Dimmer	SF10P	0-10v	1	16	22	100	1	>1S
Eaton	Decorator Dimmer	DF10P	0-10v	1	16	22	100	1	>1S
Leviton	Illumatech	IP710-DL	0-10v	1	16	20	100	1	>1S
Lutron	NTFTV	NOVA T	0-10v	1	25	58	100	1	>1S
Lutron	DIVA	DVTV	0-10v	1	25	58	100	1	>1S
Eaton	iLumin	SC277-06	0-10v	1	25	58	100	1	>1S
Eaton	Greengate	CK4A	0-10v	1	32	72	100	1	>1S

7000 Lumens / 1400mA / DE010

Dimmer Make	Dimmer Series	Dimmer Model #	Types of Dimmer	Minimum Lamps or Luminaires (per circuit)	Maximum Recommended Luminaires (per circuit) at 120V	Maximum Recommended Luminaires (per circuit) at 277V	Max Dimming percentage (%)	Min Dimming percentage (%)	Low End Start Time
Eaton	Slide Dimmer	SF10P	0-10v	1	12	17	100	1	>1S
Eaton	Decorator Dimmer	DF10P	0-10v	1	12	17	100	1	>1S
Leviton	Illumatech	IP710-DL	0-10v	1	12	16	100	1	>1S
Lutron	NTFTV	NOVA T	0-10v	1	20	44	100	1	>1S
Lutron	DIVA	DVTV	0-10v	1	20	44	100	1	>1S
Eaton	iLumin	SC277-06	0-10v	1	20	44	100	1	>1S
Eaton	Greengate	CK4A	0-10v	1	25	55	100	1	>1S

Incandescent and Electronic Low Voltage Rated Dimmers

- For Reference Only

Testing conducted by Eaton is not a substitute for and does not imply certification by an independent laboratory or any other standards certification. Refer to manufacturer specifications for more detailed information on product certifications and standards. Refer to this dimming guide notes section. Consult the dimmer manufacturer prior to installation to ensure compatibility.

Dimmer Notes:

- 1) Start time is measured at the lowest dimmer setting.
- 2) Some LED rated dimmers have a "rapid start" design used to provide a momentary power boost for LED and CFL lamps during start-up. When a LED luminaire is on a dimmer with "rapid start" the boost may cause a momentary flash of the LED lighting. This "flash" is generated by the dimmer, and may be more noticeable when the dimmer is at a low setting. A solution is available in the following Eaton dimmers which provide adjustment capability of the "rapid start": Decorator dimmer (DAL06P), Smart dimmer (AL06P), and Toggle dimmer (TAL06P). Refer to product specifications online at www.eaton.com for more details.

Dimming Guide Disclaimer:

- 1) Leviton® is a registered trademark of Leviton Manufacturing Co. Inc., Lutron® is a registered trademark of Lutron Electronics Co. Inc., Lightolier is a registered trademark of Philips Lighting, and any other brands are trade names or trademarks of their respective company, and are not associated with Eaton.
- 2) Testing conducted by Eaton is not a substitute for and does not imply certification by an independent laboratory or any other standards certification.
Refer to the manufacturer specifications for more detailed information on product certifications and standards.
- 3) This is a representative list of typical dimmers as tested by Eaton for performance with the designated LED luminaires only. Test data contained in this literature is based upon dimmers obtained in the marketplace. Information about these other manufacturers products is obtained from packaging and published information made available by the manufacturer and is deemed to be reliable, but has not been verified. Dimmer performance and perceived limitations of the dimmers are based on factors outside of Eaton's control. The specifications of these dimming controls and their conditions of use may change without notice to Eaton or any other user.
Eaton makes no specific recommendation on product selection and there are no warranties of performance or compatibility implied.
Installer must ensure proper local and national electrical codes are followed; and that the dimmer application and condition of use is per dimmer manufacturer instructions and guidelines.

Eaton's AL Series dimmers offer versatile options to set the mood and reduce energy consumption.



Note: The Rapid Start feature is used to ensure the right amount of power boost during start-up. When a dimmer with Rapid Start is turned on from a low dimmer setting, the LED lighting may exhibit a momentary flash. Select dimmer models offer an adjustment of the Rapid Start feature. The user may wish to adjust this setting to reduce the boost and resulting momentary flash. If this capability is desired, the user should select dimmer models designated as "fully adjustable" or "selectable ON or OFF".

Dimmer Features	Smart dimmer (AAL06)	Decorator dimmer (DAL06P)	Slide dimmer (SAL06P)
Rapid Start feature	Selectable ON or OFF	Fully adjustable	Fixed ON
Adjustable high-end trim	•		
Adjustable low-end trim	•	•	•
Wiring configurations	Single-pole or multi-location	Single-pole or three-way	Single-pole or three-way
Color change kits	•	•	

Eaton
1121 Highway 74 South
Peachtree City, GA 30269
P: 770-486-4800
www.eaton.com/lighting

Canada Sales
5925 McLaughlin Road
Mississauga, Ontario L5R 1B8
P: 905-501-3000
F: 905-501-3172

© 2017 Eaton
All Rights Reserved
Printed in USA
Publication No. TD520054EN
January 25, 2017 10:42 AM

Eaton is a registered trademark.
All other trademarks are property of their respective owners.
Product availability, specifications, and compliances are subject to change without notice.